

Posiflex OPOS Function List

<u>Section 1. Cash Drawer</u>	<u>2</u>
<u>Section 2. Line Display</u>	<u>4</u>
<u>Section 3. POS Printer</u>	<u>6</u>
<u>Section 4. POS Keyboard</u>	<u>12</u>
<u>Section 5. Key Lock</u>	<u>13</u>
<u>Section 6. MSR</u>	<u>14</u>
<u>Section 7. Scanner</u>	<u>16</u>

Section 1. Cash Drawer

Class	Name	Type	R/W	Version	OPOS 1.8 Specification	Posiflex OPOS & CCO Control
Properties	AutoDisable	Boolean	R/W	1.2	Not Supported	X
	BinaryConversion	Long	R/W		Not Supported	X
	CapPowerReporting	Long	R	1.3		O
	CapStatisticsReporting	Boolean	R	1.8		O
	CapUpdateStatistics	Boolean	R	1.8		O
	CheckHealthText	String	R	1.0		O
	Claimed	Boolean	R	1.0		O
	DataCount	Long	R	1.2	Not Supported	X
	DataEventEnabled	Boolean	R/W	1.0	Not Supported	X
	DeviceEnabled	Boolean	R/W	1.0		O
	FreezeEvents	Boolean	R/W	1.0		O
	OpenResult	Long	R			O
	OutputID	Long	R	1.0	Not Supported	X
	PowerNotify	Long	R/W	1.3		X
	PowerState	Long	R	1.3		X
	ResultCode	Long	R			O
	ResultCodeExtended	Long	R			O
	State	Long	R	1.0		O
	ControlObjectDescription	String	R	1.0		O
	ControlObjectVersion	Long	R	1.0		O
	ServiceObjectDescription	String	R	1.0		O
	ServiceObjectVersion	Long	R	1.0		O
	DeviceDescription	String	R	1.0		O
	DeviceName	String	R	1.0		O
	CapStatus	Boolean	R	1.0		O
	CapStatusMultiDrawerDetected	Boolean	R	1.5		O
	DrawerOpened	Boolean	R	1.0		O
Methods	<i>Open</i>			1.0		O
	<i>Close</i>			1.0		O
	<i>ClaimDevice</i>			1.0		O
	<i>ReleaseDevice</i>			1.0		O
	<i>CheckHealth</i>			1.0		O
	ClearInput				Not Supported	X
	ClearOutput				Not Supported	X
	DirectIO			1.0		X
	<i>ResetStatistics</i>			1.8		O
	<i>RetrieveStatistics</i>			1.8		O
	<i>UpdateStatistics</i>			1.8		O
	OpenDrawer			1.0		O
	WaitForDrawerClose			1.0		O
Events	DataEvent				Not Supported	X
	DirectIOEvent			1.0		X

Section 1. Cash Drawer

	ErrorEvent				Not Supported	X
	OutputCompleteEvent				Not Supported	X
	StatusUpdateEvent			1.0		O

Section 2. Line Display

Name	Type	R/W	OPOS 1.6 Specification	Posiflex OPOS & CCO Control
AutoDisable	Boolean	R/W	Not Supported	X
BinaryConversion	Long	R/W		O
CapPowerReporting	Long	R		FALSE
CheckHealthText	String	R		O
Claimed	Boolean	R		O
DataCount	Long	R	Not Supported	X
DataEventEnabled	Boolean	R/W	Not Supported	X
DeviceEnabled	Boolean	R/W		O
FreezeEvents	Boolean	R/W		X
OpenResult	Long	R		O
OutputID	Long	R	Not Supported	X
PowerNotify	Long	R/W		X
PowerState	Long	R		X
ResultCode	Long	R		O
ResultCodeExtended	Long	R		O
State	Long	R		O
ControlObjectDescription	String	R		O
ControlObjectVersion	Long	R		O
ServiceObjectDescription	String	R		O
ServiceObjectVersion	Long	R		O
DeviceDescription	String	R		O
DeviceName	String	R		O
CapBlink	Long	R		BLINKALL
CapBlinkRate	Boolean	R		TRUE
CapBrightness	Boolean	R		TRUE
CapCharacterSet	Long	R		ASCII / KANA
CapCursorType	Long	R		NONE
CapCustomGlyph	Boolean	R		FALSE
CapDescriptors	Boolean	R		FALSE
CapHMarquee	Boolean	R		FALSE
CapICharWait	Boolean	R		FALSE
CapReadBack	Long	R		NONE
CapReverse	Long	R		NONE
CapVMarquee	Boolean	R		FALSE
BlinkRate	Long	R/W		O
DeviceWindows	Long	R		0
DeviceRows	Long	R		2
DeviceColumns	Long	R		20
DeviceDescriptors	Long	R		0
DeviceBrightness	Long	R/W		O
CharacterSet	Long	R/W		O
CharacterSetList	String	R		O
CurrentWindow	Long	R/W		X

Section 2. Line Display

Rows	Long	R		O
Columns	Long	R		O
CursorRow	Long	R/W		O
CursorColumn	Long	R/W		O
CursorType	Long	R/W		O
CursorUpdate	Boolean	R/W		X
MarqueeType	Long	R/W		X
MarqueeFormat	Long	R/W		X
MarqueeUnitWait	Long	R/W		X
MarqueeRepeatWait	Long	R/W		X
InterCharacterWait	Long	R/W		X
CustomGlyphList	String	R		X
GlyphHeight	Long	R		X
GlyphWidth	Long	R		X
<i>ResetStatistics</i>			1.8	O
<i>RetrieveStatistics</i>			1.8	O
<i>UpdateStatistics</i>			1.8	O
<i>Open</i>				O
<i>Close</i>				O
<i>ClaimDevice</i>				O
<i>ReleaseDevice</i>				O
<i>CheckHealth</i>				O
ClearInput			Not Supported	X
ClearOutput			Not Supported	X
DirectIO				O
DisplayText				O
DisplayTextAt				O
ClearText				O
ScrollText				X
SetDescriptor				X
ClearDescriptors				X
CreateWindow				X
DestroyWindow				X
RefreshWindow				X
ReadCharacterAtCursor				X
DefineGlyph				X
DataEvent			Not Supported	X
DirectIOEvent				X
ErrorEvent			Not Supported	X
OutputCompleteEvent			Not Supported	X
StatusUpdateEvent				X

Section 3. POS Printer

Class	Name	Type	R/W	Version	OPOS 1.8 Specification	Posiflex OPOS & CCO Control
Properties	AutoDisable	Boolean	R/W	1.2	Not Supported	X
	BinaryConversion	Long	R/W			O
	CapPowerReporting	Long	R	1.3		O
	CapStatisticsReporting	boolean	R	1.8		O
	CapUpdateStatistics	boolean	R	1.8		O
	CheckHealthText	String	R	1.0		O
	Claimed	Boolean	R	1.0		O
	DataCount	Long	R	1.2	Not Supported	X
	DataEventEnabled	Boolean	R/W	1.0	Not Supported	X
	DeviceEnabled	Boolean	R/W	1.0		O
	FreezeEvents	Boolean	R/W	1.0		O
	OutputID	Long	R	1.0		O
	PowerNotify	Long	R/W	1.3		X
	PowerState	Long	R	1.3		X
	ResultCode	Long	R			O
	ResultCodeExtended	Long	R			O
	State	Long	R	1.0		O
	ControlObjectDescription	String	R	1.0		O
	ControlObjectVersion	Long	R	1.0		O
	ServiceObjectDescription	String	R	1.0		O
	ServiceObjectVersion	Long	R	1.0		O
	DeviceDescription	String	R	1.0		O
	DeviceName	String	R	1.0		O
	CapCharacterSet	Long	R	1.1		O
	CapConcurrentJrnRec	Boolean	R	1.0		O
	CapConcurrentJrnSlp	Boolean	R	1.0		O
	CapConcurrentRecSlp	Boolean	R	1.0		O
	CapCoverSensor	Boolean	R	1.0		O
	CapMapCharacterSet:	Boolean	R	1.7		O
	CapTransaction	Boolean	R	1.1		O
	CapJrnPresent	Boolean	R	1.0		O
	CapJrn2Color	Boolean	R	1.0		O
	CapJrnBold	Boolean	R	1.0		O
	CapJrnDhigh	Boolean	R	1.0		O
	CapJrnDwide	Boolean	R	1.0		O
	CapJrnDwideDhigh	Boolean	R	1.0		O
	CapJrnEmptySensor	Boolean	R	1.0		O
	CapJrnItalic	Boolean	R	1.0		O
	CapJrnNearEndSensor	Boolean	R	1.0		O
	CapJrnUnderline	Boolean	R	1.0		O
	CapJrnCartridgeSensor:	Long	R	1.5		O
	CapJrnColor:	Long	R	1.5		O
	CapRecPresent	Boolean	R	1.0		O

Section 3. POS Printer

	CapRec2Color	Boolean	R	1.0		O
	CapRecBarCode	Boolean	R	1.0		O
	CapRecBitmap	Boolean	R	1.0		O
	CapRecBold	Boolean	R	1.0		O
	CapRecDhigh	Boolean	R	1.0		O
	CapRecDwide	Boolean	R	1.0		O
	CapRecDwideDhigh	Boolean	R	1.0		O
	CapRecEmptySensor	Boolean	R	1.0		O
	CapRecItalic	Boolean	R	1.0		O
	CapRecLeft90	Boolean	R	1.0		O
	CapRecNearEndSensor	Boolean	R	1.0		O
	CapRecPapercut	Boolean	R	1.0		O
	CapRecRight90	Boolean	R	1.0		O
	CapRecRotate180	Boolean	R	1.0		O
	CapRecStamp	Boolean	R	1.0		O
	CapRecUnderline	Boolean	R	1.0		O
	CapRecCartridgeSensor:	Long	R	1.5		O
	CapRecColor:	Long	R	1.5		O
	CapRecMarkFeed:	Long	R	1.5		O
	CapSlpPresent	Boolean	R	1.0		O
	CapSlpFullslip	Boolean	R	1.0		O
	CapSlp2Color	Boolean	R	1.0		O
	CapSlpBarCode	Boolean	R	1.0		O
	CapSlpBitmap	Boolean	R	1.0		O
	CapSlpBold	Boolean	R	1.0		O
	CapSlpDhigh	Boolean	R	1.0		O
	CapSlpDwide	Boolean	R	1.0		O
	CapSlpDwideDhigh	Boolean	R	1.0		O
	CapSlpEmptySensor	Boolean	R	1.0		O
	CapSlpItalic	Boolean	R	1.0		O
	CapSlpLeft90	Boolean	R	1.0		O
	CapSlpNearEndSensor	Boolean	R	1.0		O
	CapSlpRight90	Boolean	R	1.0		O
	CapSlpRotate180	Boolean	R	1.0		O
	CapSlpUnderline	Boolean	R	1.0		O
	CapSlpBothSidesPrint:	Boolean	R	1.5		O
	CapSlpCartridgeSensor:	Long	R	1.5		O
	CapSlpColor:	Long	R	1.5		O
	AsyncMode	Boolean	R/W	1.0		O
	CartridgeNotify	Long	R/W	1.5		O
	CharacterSet	Long	R/W	1.0		O
						O
	CharacterSetList	String	R	1.0		
	CoverOpen	Boolean	R	1.0		O

Section 3. POS Printer

ErrorLevel	Long	R	1.1		O
ErrorStation	Long	R	1.0		O
ErrorString	String	R	1.1		O
FontTypefaceList	String	R	1.1		O
FlagWhenIdle	Boolean	R/W	1.0		O
MapCharacterSet	Boolean	R/W	1.7		O
MapMode	Long	R/W	1.0		O
RotateSpecial	Long	R/W	1.1		O
JrnLineChars	Long	R/W	1.0		X
JrnLineCharsList	String	R	1.0		X
JrnLineHeight	Long	R/W	1.0		X
JrnLineSpacing	Long	R/W	1.0		X
JrnLineWidth	Long	R	1.0		X
JrnLetterQuality	Boolean	R/W	1.0		X
JrnEmpty	Boolean	R	1.0		X
JrnNearEnd	Boolean	R	1.0		X
JrnCartridgeState:	Long	R	1.5		O
JrnCurrentCartridge:	Long	R	1.5		O
RecLineChars	Long	R/W	1.0		O
RecLineCharsList	String	R	1.0		O
RecLineHeight	Long	R/W	1.0		O
RecLineSpacing	Long	R/W	1.0		O
RecLineWidth	Long	R	1.0		O
RecLetterQuality	Boolean	R/W	1.0		X
RecEmpty	Boolean	R	1.0		X
RecNearEnd	Boolean	R	1.0		X
RecSidewaysMaxLines	Long	R	1.0		O
RecSidewaysMaxChars	Long	R	1.0		O
RecLinesToPaperCut	Long	R	1.0		O
RecBarCodeRotationList	String	R	1.0		O
RecBitmapRotationList:	String	R	1.7		O
RecCartridgeState:	Long	R	1.5		O
RecCurrentCartridge:	Long	R	1.5		O
SlpLineChars	Long	R/W	1.0		X
SlpLineCharsList	String	R	1.0		X
SlpLineHeight	Long	R/W	1.0		X
SlpLineSpacing	Long	R/W	1.0		X
SlpLineWidth	Long	R	1.0		X
SlpLetterQuality	Boolean	R/W	1.0		X
SlpEmpty	Boolean	R	1.0		X
SlpNearEnd	Boolean	R	1.0		X
SlpSidewaysMaxLines	Long	R	1.0		X
SlpSidewaysMaxChars	Long	R	1.0		X
SlpMaxLines	Long	R	1.0		X

Section 3. POS Printer

	SlpLinesNearEndToEnd	Long	R	1.0		X
	SlpBarCodeRotationList	String	R	1.1		X
	SlpBitmapRotationList:	String	R	1.7		O
	SlpPrintSide:	Long	R	1.5		O
	SlpCartridgeState:	Long	R	1.5		O
	SlpCurrentCartridge:	Long	R/W	1.5		O
Methods	<i>Open</i>			1.0		O
	<i>Close</i>			1.0		O
	<i>ClaimDevice</i>			1.0		O
	<i>ReleaseDevice</i>			1.0		O
	<i>CheckHealth</i>			1.0		O
	ClearInput				Not Supported	X
	ClearOutput			1.0		O
	DirectIO			1.0		X
	<i>resetStatistics</i>			1.8		O
	<i>retrieveStatistics</i>			1.8		O
	<i>updateStatistics</i>			1.8		O
	BeginInsertion			1.0		X
	EndInsertion			1.0		X
	BeginRemoval			1.0		X
	EndRemoval			1.0		X
	changePrintSide			1.5		X
	CutPaper			1.0		O
	markFeed			1.5		X
	RotatePrint			1.0		O
	PrintBarCode			1.0		O
	PrintBitmap			1.0		O
	PrintNormal			1.0		O
	PrintTwoNormal			1.0		X
	PrintImmediate			1.0		O
	TransactionPrint			1.0		O
	ValidateData			1.0		O
	SetBitmap			1.0		O
	SetLogo			1.0		O
	<i>ResetStatistics</i>			1.8		O
	<i>RetrieveStatistics</i>			1.8		O
	<i>UpdateStatistics</i>			1.8		O
Events	DataEvent				Not Supported	X
	DirectIOEvent					X
	ErrorEvent					X
	OutputCompleteEvent					O
	StatusUpdateEvent					O
	Escape Sequential					O

Section 3. POS Printer

Escape Sequential

Name	Data	Remarks
Paper cut	ESC #P	Cuts receipt paper. The character '#' is replaced by an ASCII decimal string telling the percentage cut desired. If '#' is omitted, then a full cut is performed. For example:
Feed and Paper cut	ESC #fP	Cuts receipt paper, after feeding the paper by the RecLinesToPaperCut lines. The character '#' is defined
Feed, Paper cut, and	ESC #sP	Cuts and stamps receipt paper, after feeding the paper by the RecLinesToPaperCut lines. The character '#' is defined by the "Paper cut" escape sequence.
Fire stamp	ESC sL	Fires the stamp solenoid, which usually contains a graphical store emblem.
Print bitmap	ESC #B	Prints the pre-stored bitmap. The character '#' is replaced
Print top logo	ESC tL	Prints the pre-stored top logo.
Print bottom logo	ESC bL	Prints the pre-stored bottom logo.
Feed lines	ESC #lF	Feed the paper forward by lines. The character '#' is replaced by an ASCII decimal string telling the number of
Feed units	ESC #uF	Feed the paper forward by mapping mode units. The character '#' is replaced by an ASCII decimal string telling the number of units to be fed. If '#' is omitted, then one unit is fed.
Feed reverse	ESC #rF	Feed the paper backward. The character '#' is replaced by an ASCII decimal string telling the number of lines to be fed. If '#' is omitted, then one line is fed.
Font typeface selection	ESC #Ft	Selects a new typeface for the following data. Values for the character '#' are: 0 = Default typeface. 1 = Select first typeface from the FontTypefaceList property. 2 = Select second typeface from the FontTypefaceList property. And so on.
Bold	ESC bC	Prints in bold or double-strike.
Underline	ESC #uC	Prints with underline. The character '#' is replaced an ASCII decimal string telling the thickness underline in printer dot units. If '#' is omitted, printer-specific default thickness is used.
Italic	ESC iC	Prints in italics.
Reverse video	ESC rvC	Prints in a reverse video format.
Single high	ESC 1C	Prints normal size.
Double wide	ESC 2C	Prints double-wide characters.
Double high	ESC 3C	Prints double-high characters.
Double high	ESC 4C	Prints double-high/double-wide characters.

Section 3. POS Printer

Scale horizontally	ESC #hC		Prints with the width scaled '#' times the normal size,where '#' is replaced by an ASCII decimal string.
Scale vertically	ESC #vC		Prints with the height scaled '#' times the normal size,where '#' is replaced by an ASCII decimal string.
RGB Color	ESC #fC		Prints in # color. The character '#' is replaced by an ASCII decimal string indicating the additive amount of RGB to produce the desired color. There are 3 digits each of Red, Green, and Blue elements. Valid values range from "000" to "255". (E.g., "255255000" represents yellow). Color Matching to the subtractive percentage of CMY (Cyan, Magenta and Yellow color components) to
SubScript	ESC tbC		Prints SubScript characters.
SuperScript	ESC tpC		Prints SuperScript characters.
Center	ESC cA		Aligns following text in the center.
Right justify	ESC rA		Aligns following text at the right.
Normal	ESC N		Restores printer characteristics to normal condition.

Section 4. POS Keyboard

Class	Name	Type	R/W	OPOS 1.3 Specification	Posiflex OPOS & CCO Control
Properties	AutoDisable	Boolean	R/W		O
	BinaryConversion	Long	R/W	Not Supported	X
	CapPowerReporting	Long	R		FALSE
	CheckHealthText	String	R		O
	Claimed	Boolean	R		O
	DataCount	Long	R		O
	DataEventEnabled	Boolean	R/W		O
	DeviceEnabled	Boolean	R/W		O
	FreezeEvents	Boolean	R/W		O
	OutputID	Long	R	Not Supported	X
	PowerNotify	Long	R/W		X
	PowerState	Long	R		X
	ResultCode	Long	R		O
	ResultCodeExtended	Long	R		O
	State	Long	R		O
	ControlObjectDescription	String	R		O
	ControlObjectVersion	Long	R		O
	ServiceObjectDescription	String	R		O
	ServiceObjectVersion	Long	R		O
	DeviceDescription	String	R		O
	DeviceName	String	R		O
	CapKeyUp	Boolean	R		TRUE
	EventTypes	Long	R/W		O
	POSKeyData	Long	R		O
	POSKeyEventType	Long	R		O
Methods	Open				O
	Close				O
	ClaimDevice				O
	ReleaseDevice				O
	CheckHealth				O
	ClearInput				O
	ClearOutput			Not Supported	X
	DirectIO				X
Events	DataEvent				O
	DirectIOEvent				X
	ErrorEvent				X
	OutputCompleteEvent			Not Supported	X
	StatusUpdateEvent				X

Section 5. Key lock

Class	Name	Type	R/W	OPOS 1.6 Specification	Posiflex OPOS & CCO Control
Properties	AutoDisable	Boolean	R/W	Not Supported	X
	BinaryConversion	Long	R/W	Not Supported	X
	CapPowerReporting	Long	R		FALSE
	CheckHealthText	String	R		O
	Claimed	Boolean	R		O
	DataCount	Long	R	Not Supported	X
	DataEventEnabled	Boolean	R/W	Not Supported	X
	DeviceEnabled	Boolean	R/W		O
	FreezeEvents	Boolean	R/W		O
	OpenResult	Long	R		O
	OutputID	Long	R	Not Supported	X
	PowerNotify	Long	R/W		X
	PowerState	Long	R		X
	ResultCode	Long	R		O
	ResultCodeExtended	Long	R		O
	State	Long	R		O
	ControlObjectDescription	String	R		O
	ControlObjectVersion	Long	R		O
	ServiceObjectDescription	String	R		O
	ServiceObjectVersion	Long	R		O
	DeviceDescription	String	R		O
	DeviceName	String	R		O
	KeyPosition	Long	R		O
	PositionCount	Long	R		O
Methods	Open				O
	Close				O
	ClaimDevice				O
	ReleaseDevice				O
	CheckHealth				O
	ClearInput			Not Supported	X
	ClearOutput			Not Supported	X
	DirectIO				X
	WaitForKeylockChange				O
Events	DataEvent			Not Supported	O
	DirectIOEvent				X
	ErrorEvent			Not Supported	X
	OutputCompleteEvent			Not Supported	X
	StatusUpdateEvent				X

Section 6. MSR

Name	Type	R/W	OPOS 1.6 Specification	Posiflex OPOS & CCO Control
AutoDisable	Boolean	R/W		O
BinaryConversion	Long	R/W	Not Supported	X
CapPowerReporting	Long	R		FALSE
CheckHealthText	String	R		O
Claimed	Boolean	R		O
DataCount	Long	R		O
DataEventEnabled	Boolean	R/W		O
DeviceEnabled	Boolean	R/W		O
FreezeEvents	Boolean	R/W		O
OpenResult	Long	R		O
OutputID	Long	R		O
PowerNotify	Long	R/W		X
PowerState	Long	R		X
ResultCode	Long	R		O
ResultCodeExtended	Long	R		O
State	Long	R		O
ControlObjectDescription	String	R		O
ControlObjectVersion	Long	R		O
ServiceObjectDescription	String	R		O
ServiceObjectVersion	Long	R		O
DeviceDescription	String	R		O
DeviceName	String	R		O
CapISO	Boolean	R		TRUE
CapJISOne	Boolean	R		TRUE
CapJISTwo	Boolean	R		TRUE
CapTransmitSentinels	Boolean	R		TRUE
TracksToRead	Long	R/W		O
DecodeData	Boolean	R/W		O
ParseDecodeData	Boolean	R/W		O
ErrorReportingType	Long	R/W		O
Track1Data	String	R		O
Track2Data	String	R		O
Track3Data	String	R		O
Track4Data	String	R		O
AccountNumber	String	R		O
ExpirationDate	String	R		O
Title	String	R		O
FirstName	String	R		O
MiddleInitial	String	R		O
Surname	String	R		O
Suffix	String	R		O
ServiceCode	String	R		O
Track1DiscretionaryData	String	R		O

Section 6. MSR

Track2DiscretionaryData	String	R		O
TransmitSentinels	Boolean	R/W		O
<i>Open</i>				O
<i>Close</i>				O
<i>ClaimDevice</i>				O
<i>ReleaseDevice</i>				O
<i>CheckHealth</i>				O
ClearInput				X
ClearOutput			Not Supported	X
DirectIO				X
<i>ResetStatistics</i>			1.8	O
<i>RetrieveStatistics</i>			1.8	O
<i>UpdateStatistics</i>			1.8	O
DataEvent				O
DirectIOEvent				X
ErrorEvent				X
OutputCompleteEvent			Not Supported	X
StatusUpdateEvent				X

Section 7. Scanner(Bar code reader)

Class	Name	Type	R/W	OPOS 1.6 Specification	Posiflex OPOS & CCO Control
Properties	AutoDisable	Boolean	R/W		X
	BinaryConversion	Long	R/W	Not Supported	X
	CapPowerReporting	Long	R		FALSE
	CheckHealthText	String	R		O
	Claimed	Boolean	R		O
	DataCount	Long	R		O
	DataEventEnabled	Boolean	R/W		O
	DeviceEnabled	Boolean	R/W		O
	FreezeEvents	Boolean	R/W		O
	OpenResult	Long	R		O
	OutputID	Long	R	Not Supported	X
	PowerNotify	Long	R/W		X
	PowerState	Long	R		X
	ResultCode	Long	R		O
	ResultCodeExtended	Long	R		O
	State	Long	R		O
	ControlObjectDescription	String	R		O
	ControlObjectVersion	Long	R		O
	ServiceObjectDescription	String	R		O
	ServiceObjectVersion	Long	R		O
	DeviceDescription	String	R		O
	DeviceName	String	R		O
	DecodeData	String	R		O
	ScanData	String	R		O
	ScanDataLabel	String	R		O
	ScanDataType	Long	R		O
Methods	Open				
	Close				O
	ClaimDevice				O
	ReleaseDevice				O
	CheckHealth				O
	ClearInput				O
	ClearOutput			Not Supported	X
	DirectIO				X
Events	DataEvent				O
	DirectIOEvent				X
	ErrorEvent				X
	OutputCompleteEvent			Not Supported	X
	StatusUpdateEvent				X